



Printed Pages : 3

TEE-405

(Following Paper ID and Roll No. to be filled in your Answer Book)

**PAPER ID : 2049**

Roll No.

--	--	--	--	--	--	--	--	--	--

## B. Tech.

(SEM. IV) EXAMINATION, 2007-08

### ELECTRICAL MACHINES

Time : 3 Hours]

[Total Marks : 100

Note : Attempt **all** questions.

1 Attempt any **four** parts of the following : **4×5=20**

- Describe the operation of a single-phase transformer, explaining clearly the functions of different parts.
- Explain how emf induced in a winding of transformer is related to the number of turns and the flux density in the core.
- Explain polarity test of single phase transformer with suitable circuit diagram.
- Derive an expression for saving in conductor material in an autotransformer over a two-winding transformer of same rating.
- What are distinguishing features of Y-Y and Y- $\Delta$  3-phase connections ?
- Draw the Scott connection of transformers and mark the terminals. What are the applications of Scott connection ?



2 Attempt any **two** parts of the following :  $2 \times 10 = 20$

- (a) Explain the principle of operation of dc machine. Derive the expression for the back emf in a dc motor. Briefly explain the role it plays in starting and running of the motor.
- (b) A dc shunt generator running at 500 rpm delivers 50 kW at 250 V. It has armature resistance of  $0.02 \Omega$  and field winding resistance of  $50 \Omega$ . Calculate the speed of the machine running as a shunt motor and taking a power of 50 kW at 250 V.
- (c) Why is it necessary to use a starter for starting a dc motor ? Draw the diagram of a three-point starter and explain the function of each component.

3 Attempt any **two** parts of the following :  $2 \times 10 = 20$

- (a) Derive the equation for the torque developed by a three - phase induction motor. Draw a typical torque-slip curve and deduce the condition for maximum torque.
- (b) A 4 pole, 3-phase, 50 Hz, 230 V induction motor has a delta connected stator and a star connected rotor. Each phase of rotor winding has one - fourth the number of turns of each stator. The full load speed is 1455 rpm. The rotor resistance is  $0.3 \Omega$  and rotor stand still reactance is  $1.0 \Omega$  per phase. The rotor and stator windings are similar. Stator losses are equal to 50 watts. Friction and windage losses are equal to 30 W.
- Calculate :**
- blocked rotor voltage per phase.
  - rotor current per phase under full load running condition.
  - total rotor power input at full load.
  - rotor gross loss at full load
  - total mechanical power developed.

- (c) Explain why a starter is needed for starting an induction motor. With the help of a circuit diagram, explain how a star-delta starter is used for starting an induction motor.

4 Attempt any **two** parts of the following : **2×10=20**

- (a) Explain the constructional details of a synchronous machine giving reasons for making two different types of rotors.
- (b) A 3-phase, star connected alternator is rated at 1600 kVA, 13500 V. The armature effective resistance and synchronous reactance are  $1.5 \Omega$  and  $30 \Omega$  respectively per phase. Calculate the percentage regulation for a load of 1280 kW at power factor of (i) 0.8 lagging and (ii) 0.8 leading.
- (c) Explain the effect of change of excitation of a synchronous motor on its :  
(i) armature current and (ii) power factor and also draw phasor diagram.

5 Attempt any **two** parts of the following : **2×10=20**

- (a) Explain the working principle of capacitor start single - phase induction motor. Why should be the auxiliary winding in a capacitor start motor be disconnected after the motor has picked up speed?
- (b) Explain the operation of a stepper motor. What are its advantages and disadvantages ?
- (c) What is two-phase servomotor ? Describe its construction and operation.

