Roll No:

B. Tech. (SEM V) THEORY EXAMINATION 2021-22 DIGITAL SIGNAL PROCESSING

Time: 3 Hours

Total Marks: 100

Note: 1. Attempt all Sections. If require any missing data; then choose suitably.

SECTION A

Attempt all questions in brief. 1.

 $2 \times 10 = 20$

- Define the Recursive and Non-Recursive systems. a.
- Enlist the Condition for Linear Phase FIR digital filter with 5 Number of b. samples.
- Differentiate Butterworth Low Pass Filter with Chebyshev LPF in terms of c. Filter Order.
- Evaluate the value of $C_3(x)$, Chebyshev Polynomial. d.
- Demonstrate the term Gibb's Phenomenon with schematic diagram. e.
- Explain the terms Truncation Error & Round off Error with suitable examples. f.
- Evaluate the DFT for the sequence [1, 2, 7, 3]. g.
- Find out the total no of Complex additions and Complex multiplications h. required for calculating 8-point Conventional DFT & by using butterfly structure DIT-FFT.
- Explain the term Decimation with suitable example. i.
- 10×32×30 Find the output of the sequence [1 2 3] after up sampling by a factor N=3. j.

2. Attempt any three of the following:

Realize the given H(z) for using ladder structure.

$$H(z) = \frac{2 + 8z^{-1} + 6z^{-2}}{1 + 8z^{-1} + 12z^{-2}}$$

Design Digital Butterworth filter to satisfy the following constraints using b. bilinear transformation method, the sampling Interval is 2 second: assume missing data if required:

one data if required:

$$0.52 \leq |H(e^{jw})| \leq 1$$

$$H(e^{jw})| \leq 0.5$$

$$0.52 \leq |H(e^{jw})| \leq 0.5$$

$$0.52 \leq |H(e^{jw})| \leq 0.5$$

- c. Explain the concept of the Limit Cycle Oscillations & dead band effect with suitable example.
- Calculate the circular convolution using graphical method for d. x(n) = [1,2,3,4] and h(n) = [4,22,1].
- Summarize QMF & Explain analytical and synthesis filter bank with aliasing e. free filter bank.

SECTION C

3. Attempt any one part of the following:

 $10 \times 1 = 10$

- Describe the linear phase FIR systems, &For h (n) = [1/2, 1/3, 1/5, 1/3, 1/2]Realize H(z) of the Linear Phase FIR system for the given impulse response.
- Find out the direct form-I & direct form-II realization of a discrete-time system represented by the transfer function



Roll No:

$$y(n) = -\frac{13}{12}y(n-1) - \frac{9}{24}y(n-2) - \frac{1}{24}y(n-3) + x(n) + 4x(n-1) + 3x(n-2)$$

Attempt any one part of the following: 4.

 $10 \times 1 = 10$

Design Chebyshev Digital LPF filter to satisfy the following constraints using Impulse Invariant method.

$$\begin{array}{ll} 0.9 & \leq \left|\begin{array}{ll} H(e^{jw}) \end{array}\right| \leq 1 & , 0 \leq w \leq 0.25\pi \\ \left|\begin{array}{ll} H(e^{jw}) \end{array}\right| \leq 0.24 & , 0.5\pi \leq w \leq \pi \end{array}$$

Design Chebyshev Digital LPF filter to satisfy the following constraints using (b) Bilinear Transformation method, assume that the sampling time is one second.

$$0.707 \le |H(e^{jw})| \le 1$$
 $0.1,0.5\pi \le w \le \pi$ 0.2π

5. Attempt any one part of the following:

 $10 \times 1 = 10$

A low Pass filter is to be designed with the following specifications: (a)

$$H_d(e^{jw}) = \begin{cases} e^{-2jw} & , -\pi/4 \le w \le \pi/4 \\ 0 & , \text{otherwise} \end{cases}$$

155.241.AT Using Rectangular window function, Find the Filter coefficients & Frequency spectrum of the designed filter. spectrum of the designed filter.

(b) Design a Filter with

$$H_d(e^{|w|}) = \begin{cases} e^{-3/w} & , -\pi/4 \le w \le \pi/4 \\ 0 & , \pi/4 \le w \le \pi \end{cases}$$

6.

 $10 \times 1 = 10$

Attempt any one part of the following:

(a) Using DIF FFT find X (k), for x (n) = 2ⁿ⁺¹, for N=83

(b) Derive & solve the DIT FFT algorithm

7. Attempt any one part of the following:

pt any one part of the following:

Explain the block diagrammatic presentation of DSP processor, with its architecture addressing formation f(x)(a) architecture, addressing formats and its commercial usages.

Write a short note on LMS Algorithm. (b)