

Roll No:

| | | | | | | | | | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|

BTECH
(SEM V) THEORY EXAMINATION 2024-25
OPTICAL COMMUNICATION

TIME: 3 HRS

M.MARKS: 70

Note: Attempt all Sections. In case of any missing data; choose suitably.

SECTION A

1. Attempt all questions in brief.

2 x 07 = 14

| Q no. | Question | CO | Level |
|-------|--|----|-------|
| a. | Why does fiber optics promise to be the technology of choice for local area network? | 1 | 2 |
| b. | Calculate the velocity of light within glass having refractive index (n) equal to 1.5? | 1 | 3 |
| c. | Specify three peak wavelengths for the transparent windows in modern optical fibers. | 2 | 1 |
| d. | Define the term Photoluminescence. | 4 | 1 |
| e. | Suppose a laser diode radiates red light with wavelength of 650 nm. Calculate the energy of a single photon? | 3 | 3 |
| f. | How does photo diode converts light into electrical signal? | 5 | 2 |
| g. | Differentiate between coherent and non-coherent detection technique. | 5 | 2 |

SECTION B

2. Attempt any three of the following:

07 x 3 = 21

| Q no. | Question | CO | Level |
|-------|--|----|-------|
| a. | Draw a block diagram of fiber optic communications system and describe the function of each component. | 1 | 2 |
| b. | Define the term dispersion in optical fiber. How much will a light pulse spread after travelling along 5 km of a step index fiber whose numerical aperture is 0.275 and refractive index of the core is 1.487? | 2 | 3 |
| c. | With suitable energy band diagram explain the mechanisms of absorption, spontaneous, and stimulated emission in a compound semiconductor? | 3 | 3 |
| d. | Explain the principle of operation of a quantum well laser diode? | 4 | 2 |
| e. | With suitable block diagram explain Wavelength Division Multiplexing technique in optical fiber communication? | 5 | 2 |

SECTION C

3. Attempt any one part of the following:

07 x 1 = 07

| Q no. | Question | CO | Level |
|-------|--|----|-------|
| a. | Write the significance of total internal reflection in an optical fiber. The refractive index of core and cladding of a silica fiber are 1.48 and 1.46 respectively. Calculate the critical propagation angle? Find the total acceptance angle of the fiber? | 1 | 3 |
| b. | Write short notes on: i. Dispersion shifted and dispersion flattened fiber ii. Polarization mode dispersion | 2 | 2 |



Roll No:

| | | | | | | | | | | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | | | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|--|

BTECH
(SEM V) THEORY EXAMINATION 2024-25
OPTICAL COMMUNICATION

TIME: 3 HRS

M.MARKS: 70

4. Attempt any one part of the following: 07 x 1 = 07

| Q no. | Question | CO | Level |
|-------|--|----|-------|
| a. | Explain basic techniques used to couple light from an LED into an optical fiber? Calculate the power coupled into a step index multimode fiber whose $n_1 = 1.48$ and whose $n_2 = 1.46$ if the surface light emitting diode (SLED) radiates $100 \mu\text{W}$? | 4 | 3 |
| b. | Draw a graph depicting the typical input-output relationship in a laser diode and explain what mechanisms determine the course of the graph? | 4 | 3 |

5. Attempt any one part of the following: 07 x 1 = 07

| Q no. | Question | CO | Level |
|-------|--|----|-------|
| a. | With suitable diagram explain the working of edge light emitting diode (ELED) and surface light emitting diode (SLED)? | 3 | 2 |
| b. | Write short note on: i. Dark Current ii. Bit Error Rate | 5 | 2 |

6. Attempt any one part of the following: 07 x 1 = 07

| Q no. | Question | CO | Level |
|-------|---|----|-------|
| a. | How does responsivity depend on the wavelength of an optical signal? The responsivity of a photodiode is 0.85 A/W and the input power saturation is 1.5 mW . Calculate the photocurrent if the incident power is 1 mW ? | 4 | 3 |
| b. | Write the major advantages of Avalanche Photo Diode over p-i-n photodiode. | 4 | 2 |

7. Attempt any one part of the following: 07 x 1 = 07

| Q no. | Question | CO | Level |
|-------|---|----|-------|
| a. | What do you mean by mode coupling? Explain the various irregularities in the fiber of its causes. | 2 | 2 |
| b. | Draw a functional block diagram of a receiver and briefly explain the function of each component? | 5 | 2 |